



## RESIDUAL POWER PERCENTAGE (Cable Run Efficiency)

Given a power fed to the X value (any value expressed in Watts), the actual power output of the cable is shown in the table in the form of remaining percentage. (for example, if we use a cable such as M&P-HYPERFLEX 13, entering 1000 Watts over a length of 35m, at a frequency of 144 MHz, there remains 74.7 % of 1000). **For maximum applicable power, see the Power Handling of the cable concerned.** From these values, have already been deducted the SRL values, typical of each one of our models, for the respective frequencies. **REMEMBER: Make sure to match the line accurately!**

		M&P-HYPERFLEX 13/.500"													
feet		16,4	32,8	49,2	65,6	82	114,8	164	246	328	426,5	524,9	656,2	984,2	
meters		5	10	15	20	25	35	50	75	100	130	160	200	300	
Wave length	MHz	Useful signal output (residual power %)													
Frequencies	85.71 m	3,5	99,1	98,3	97,5	96,7	96,0	94,4	92,2	88,5	85,0	81,0	77,2	72,3	61,6
	42.85 m	7	98,9	97,8	96,8	95,8	94,9	92,9	90,1	85,5	81,2	76,3	71,7	66,0	53,6
	21.42 m	14	98,6	97,2	95,9	94,6	93,3	90,8	87,2	81,5	76,1	70,1	64,6	58,0	44,2
	10.71 m	28	98,1	96,3	94,6	92,9	91,2	87,9	83,3	76,0	69,4	62,2	55,8	48,2	33,5
	6 m	50	97,6	95,4	93,2	91,1	89,0	85,0	79,3	70,7	63,0	54,9	47,8	39,7	25,0
	2 m	144	95,8	91,9	88,2	84,6	81,2	74,7	66,0	53,6	43,6	33,9	26,4	19,0	8,2
	69 cm	430	92,7	86,1	80,0	74,3	69,0	59,5	47,6	32,9	22,7	14,5	9,3	5,1	
	23.1 cm	1296	86,8	75,8	66,1	57,7	50,4	38,3	25,4	12,6	6,1				
	12.5 cm	2400	81,9	67,5	55,6	45,8	37,7	25,4	14,0	5,0					
	10 cm	3000	79,4	63,7	51,1	40,9	32,7	20,8	10,4						
	7.5 cm	4000	76,2	58,6	45,1	34,6	26,5	15,4	6,5						
	6 cm	5000	73,4	54,4	40,2	29,6	21,8	11,6	4,2						
	5 cm	6000	70,3	50,0	35,5	25,1	17,6	8,3							
	3.75 cm	8000	65,6	43,5	28,7	18,8	12,1	4,6							
	3 cm	10.000	59,6	36,2	21,5	12,3	6,6								
	2.5 cm	12.000	55,7	31,5	17,3	8,9	3,9								

## M&P-HYPERFLEX 13 /.500" Power Handling/Temperature (in Continuous Carrier)

Wave length	MHz	Temperature C° / F°										WATT	
		-10 / 14	-5 / 23	0 / 32	10 / 50	20 / 68	30 / 86	40 / 104	50 / 122	60 / 140	70 / 158		
Frequencies	166.66 m	1,8	18000	18000	18000	18000	18000	16501	14681	12523	10365	8221	
	85.71 m	3,5	18000	18000	18000	17204	15838	14219	12650	10790	8931	7084	
	42.85 m	7	15295	14781	14346	13437	12370	11105	9880	8428	6975	5533	
	30 m	10	12880	12448	12081	11316	10417	9352	8321	7097	5874	4660	
	21.42 m	14	11037	10666	10353	9697	8927	8014	7130	6082	5034	3993	
	14.28 m	21	8873	8574	8322	7795	7176	6442	5732	4889	4047	3210	
	10.71 m	28	7682	7424	7205	6749	6213	5578	4962	4233	3503	2779	
	6 m	50	5995	5794	5624	5267	4849	4353	3873	3304	2734	2169	
	3 m	100	4327	4182	4059	3801	3500	3142	2795	2384	1973	1565	
	2.08 m	144	3709	3584	3479	3258	3000	2693	2396	2044	1691	1342	
	1.5 m	200	3327	3216	3121	2923	2691	2416	2150	1834	1518	1204	
	75 cm	400	2301	2223	2158	2021	1861	1671	1486	1268	1049	832	
	69 cm	430	2222	2147	2084	1952	1797	1613	1435	1224	1013	804	
	37.5 cm	800	1582	1529	1484	1390	1280	1149	1022	872	722	572	
	30 cm	1000	1404	1357	1317	1234	1136	1020	907	774	641	508	
	23.1 cm	1296	1217	1176	1142	1069	984	884	786	671	555	440	
	12.5 cm	2400	854	825	801	750	691	620	552	470	389	309	
	10 cm	3000	754	728	707	662	609	547	487	415	344	273	
	7.5 cm	4000	634	613	595	557	513	461	410	350	289	229	
6 cm	5000	555	536	520	487	449	403	358	306	253	201		
5 cm	6000	496	479	465	436	401	360	320	273	226	179		
4.2 cm	7000	449	434	421	395	363	326	290	247	205	162		
3.75 cm	8000	412	398	386	362	333	299	266	227	188	149		
3.3 cm	9000	380	367	356	334	307	276	245	209	173	137		
3 cm	10.000	352	340	330	309	284	255	227	194	160	127		

Do not use the cable as power supply for both direct current and 50-60 HZ mains